


IDLE-UPSWITCH (1HZ, 1HD-T, 1HD-FTE) INSPECTION

AC1UT-0

1. REMOVEIDLE - UPSWITCH

Using a screwdriver, pullout the switch then disconnect the connector.




2. INSPECTIDLE - UPSWITCH

illumination lights up.

(a) Inspect the illumination operation.
 Connect the positive (+) lead from the battery to terminal 1 and negative (-) lead to terminal 2 then check that the

If operation is not as specified, check the bulb.




(b) 1HD -FTE Engine w/Viscous Heater:

Inspect power heater indicator operation.

Connect the positive (+) lead from the battery to terminal 5 and negative (-) lead to terminal 5 then check that the indicator lights up.

If operation is not as specified, check the bulb.



(c) Inspect the idle -up switch continuity.

Check the continuity exists between terminals 3 and 4. If no continuity exists, replace the switch.

3. INSTALLIDLE - UPSWITCH